

# **SAW Components**

Data Sheet R 714





SAW Components R 714
Resonator 423,22 MHz

**Data Sheet** 


### **Features**

- 1-port resonator
- Provides reliable, fundamental mode, quartz frequency stabilization i.e. in transmitters or local oscillators

#### **Terminals**

■ Ni, gold plated

## SMD Ceramic package QCC8C



Dimensions in mm, approx. weight 0,1 g

## Pin configuration


2 Innut

6 Output, grounded in 1-port conf.

4,8 Ground (case)

1,3 float

5,7 float / ground



Туре	Ordering code	Marking and Package	Packing	
		according to	according to	
R 714	B39431-R 714-U310	C61157-A7-A56	F61074-V8023-Z000	

Electrostatic Sensitive Device (ESD)

### **Maximum ratings**

Operable temperature range	$T_{A}$	-45/+120	°C	
Storage temperature range	$T_{\rm stq}$	-45/+120	°C	
DC voltage	$V_{\rm DC}$	12	V	between any terminals
Source power	$P_{\rm s}$	0	dBm	



SAW Components R 714
Resonator 423,22 MHz

**Data Sheet** 

## Characteristics

 $\begin{array}{lll} \mbox{Reference temperature:} & T_{\mbox{A}} & = 25 \ ^{\circ}\mbox{C} \\ \mbox{Terminating Source impedance:} & Z_{\mbox{S}} & = 50 \ \Omega \\ \mbox{Terminating Load impedance:} & Z_{\mbox{L}} & = 50 \ \Omega \\ \end{array}$ 

		min.	typ.	max.	
Center frequency 1)	f <sub>c</sub>	423,145	423,22	423,295	MHz
Minimum insertion attenuation	$\alpha_{min}$	_	1,2	1,9	dB
Unloaded quality factor	$Q_U$	6000	10000	_	
Ageing of f <sub>c</sub>		_	_	±50	ppm
Equivalent circuit elements					
Motional capacitance	$C_1$	_	2,228	_	fF
Motional inductance	$L_1$	_	63,47	_	μH
Motional resistance	$R_1$	_	15	27	Ω
Parallel Capacitance 2)	$C_0$	_	3,4	_	pF
Temperature coefficient of frequency 3)	TC <sub>f</sub>	_	- 0,03	_	ppm/K <sup>2</sup>
Turnover temperature	$T_0$	0	_	30	°C

<sup>1)</sup> Center frequency is defined as maximum of the real part of the admittance

 $<sup>^{2)}</sup>$  If used in two port configuration (pin 2-input, pin 6-output)  $C_0$  is reduced by approx. 0,3 pF.

<sup>&</sup>lt;sup>3)</sup>Temperature dependence of  $f_c$ :  $f_c(T_A) = f_c(T_0)(1 + TC_f(T_A - T_0)^2)$ 



SAW Components R 714
Resonator 423,22 MHz

**Data Sheet** 

#### Published by EPCOS AG Surface Acoustic Wave Components Division, SAW CE AE PD P.O. Box 80 17 09, D-81617 München

© EPCOS AG 2001. All Rights Reserved.

As far as patents or other rights of third parties are concerned, liability is only assumed for components per se, not for applications, processes and circuits implemented within components or assemblies.

The information describes the type of component and shall not be considered as assured characteristics.

Terms of delivery and rights to change design reserved.

For questions on technology, prices and delivery please contact the sales offices of EPCOS AG or the international representatives.

Due to technical requirements components may contain dangerous substances. For information on the type in question please also contact one of our sales offices.