



Is Now Part of



**ON Semiconductor®**

To learn more about ON Semiconductor, please visit our website at

[www.onsemi.com](http://www.onsemi.com)

ON Semiconductor and the ON Semiconductor logo are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at [www.onsemi.com/site/pdf/Patent-Marking.pdf](http://www.onsemi.com/site/pdf/Patent-Marking.pdf). ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that ON Semiconductor was negligent regarding the design or manufacture of the part. ON Semiconductor is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.




# KSC5338D/KSC5338DW

## NPN Triple Diffused Planar Silicon Transistor

### Features

- High Voltage Power Switch Switching Application
- Wide Safe Operating Area
- Built-in Free-Wheeling Diode
- Suitable for Electronic Ballast Application
- Small Variance in Storage Time
- Two Package Choices : TO-220 or D<sup>2</sup>-PAK



### Absolute Maximum Ratings $T_a=25^\circ\text{C}$ unless otherwise noted

Symbol	Parameter	Value	Units
$V_{CBO}$	Collector-Base Voltage	1000	V
$V_{CEO}$	Collector-Emitter Voltage	450	V
$V_{EBO}$	Emitter-Base Voltage	12	V
$I_C$	Collector Current (DC)	5	A
$I_{CP}$	*Collector Current (Pulse)	10	A
$I_B$	Base Current (DC)	2	A
$I_{BP}$	*Base Current (Pulse)	4	A
$P_C$	Power Dissipation ( $T_C=25^\circ\text{C}$ )	75	W
$T_J$	Junction Temperature	150	$^\circ\text{C}$
$T_{STG}$	Storage Temperature	- 55 to 150	$^\circ\text{C}$

\* Pulse Test : Pulse Width = 5ms, Duty Cycle  $\leq$  10%

### Thermal Characteristics

Symbol	Parameter	Rating	Units	
$R_{\theta jc}$	Thermal Resistance	Junction to Case	1.65	$^\circ\text{C}/\text{W}$
$R_{\theta ja}$		Junction to Ambient	62.5	$^\circ\text{C}/\text{W}$
$T_L$	Maximum Lead Temperature for Soldering		270	$^\circ\text{C}$

**Electrical Characteristics**  $T_a=25^\circ\text{C}$  unless otherwise noted

Symbol	Parameter	Test Condition	Min.	Typ.	Max.	Units	
$BV_{CBO}$	Collector-Base Breakdown Voltage	$I_C=1\text{mA}, I_E=0$	1000			V	
$BV_{CEO}$	Collector-Emitter Breakdown Voltage	$I_C=5\text{mA}, I_B=0$	450			V	
$BV_{EBO}$	Emitter-Base Breakdown Voltage	$I_E=1\text{mA}, I_C=0$	12			V	
$I_{CBO}$	Collector Cut-off Current	$V_{CB}=800\text{V}, I_E=0$			10	$\mu\text{A}$	
$I_{CES}$	Collector Cut-off Current	$V_{CES}=1000\text{V}, I_{EB}=0$	$T_a=25^\circ\text{C}$		100	$\mu\text{A}$	
			$T_a=125^\circ\text{C}$		500	$\mu\text{A}$	
$I_{CEO}$	Collector Cut-off Current	$V_{CE}=450\text{V}, I_B=0$	$T_a=25^\circ\text{C}$		100	$\mu\text{A}$	
			$T_a=125^\circ\text{C}$		500	$\mu\text{A}$	
$I_{EBO}$	Emitter Cut-off Current	$V_{EB}=10\text{V}, I_C=0$			10	$\mu\text{A}$	
$h_{FE}$	DC Current Gain	$V_{CE}=1\text{V}, I_C=0.8\text{A}$	$T_a=25^\circ\text{C}$	15	25		
			$T_a=125^\circ\text{C}$	10	14		
		$V_{CE}=1\text{V}, I_C=2\text{A}$	$T_a=25^\circ\text{C}$	6	9		
			$T_a=125^\circ\text{C}$	4	6		
		$V_{CE}=2.5\text{V}, I_C=1\text{A}$	$T_a=25^\circ\text{C}$	18	25		
			$T_a=125^\circ\text{C}$	14	18		
$V_{CE(sat)}$	Collector-Emitter Saturation Voltage	$I_C=0.8\text{A}, I_B=0.08\text{A}$	$T_a=25^\circ\text{C}$		0.35	0.5	V
			$T_a=125^\circ\text{C}$		0.55	0.75	V
		$I_C=2\text{A}, I_B=0.4\text{A}$	$T_a=25^\circ\text{C}$		0.47	0.75	V
			$T_a=125^\circ\text{C}$		0.9	1.1	V
		$I_C=0.8\text{A}, I_B=0.04\text{A}$	$T_a=25^\circ\text{C}$		0.9	1.5	V
			$T_a=125^\circ\text{C}$		1.8	2.5	V
		$I_C=1\text{A}, I_B=0.2\text{A}$	$T_a=25^\circ\text{C}$		0.22	0.5	V
			$T_a=125^\circ\text{C}$		0.3	0.6	V
$V_{BE(sat)}$	Base-Emitter Saturation Voltage	$I_C=0.8\text{A}, I_B=0.08\text{A}$	$T_a=25^\circ\text{C}$		0.8	1.0	V
			$T_a=125^\circ\text{C}$		0.65	0.9	V
		$I_C=2\text{A}, I_B=0.4\text{A}$	$T_a=25^\circ\text{C}$		0.9	1.0	V
			$T_a=125^\circ\text{C}$		0.8	0.9	V
$C_{ib}$	Input Capacitance	$V_{EB}=10\text{V}, I_C=0.5\text{A}, f=1\text{MHz}$		550	750	pF	
$C_{ob}$	Output Capacitance	$V_{CB}=10\text{V}, I_E=0, f=1\text{MHz}$		60	100	pF	
$f_T$	Current Gain Bandwidth Product	$I_C=0.5\text{A}, V_{CE}=10\text{V}$		11		MHz	
$V_F$	Diode Forward Voltage	$I_F=1\text{A}, I_C=1\text{mA}, I_E=0$	$T_a=25^\circ\text{C}$		0.86	1.3	V
			$T_a=125^\circ\text{C}$		0.79		V
		$I_F=2\text{A}$	$T_a=25^\circ\text{C}$		0.95	1.5	V
			$T_a=125^\circ\text{C}$		0.88		V
$t_{fr}$	Diode Forward Recovery Time ( $di/dt=10\text{A}/\mu\text{s}$ )	$I_F=0.4\text{A}$		460		ns	
		$I_F=1\text{A}$		360		ns	
		$I_F=2\text{A}$		325		ns	
$V_{CE(DSAT)}$	Dynamic Saturation Voltage	$I_C=1\text{A}, I_{B1}=100\text{mA}$ $V_{CC}=300\text{V}$ at $1\mu\text{s}$	$T_a=25^\circ\text{C}$		8		V
			$T_a=125^\circ\text{C}$		15		V
		$I_C=1\text{A}, I_{B1}=100\text{mA}$ $V_{CC}=300\text{V}$ at $3\mu\text{s}$	$T_a=25^\circ\text{C}$		2.9		V
			$T_a=125^\circ\text{C}$		8		V
		$I_C=2\text{A}, I_{B1}=400\text{mA}$ $V_{CC}=300\text{V}$ at $1\mu\text{s}$	$T_a=25^\circ\text{C}$		9		V
			$T_a=125^\circ\text{C}$		17		V
		$I_C=2\text{A}, I_{B1}=400\text{mA}$ $V_{CC}=300\text{V}$ at $3\mu\text{s}$	$T_a=25^\circ\text{C}$		1.9		V
			$T_a=125^\circ\text{C}$		8.5		V

**Electrical Characteristics** (Continued)  $T_a=25^\circ\text{C}$  unless otherwise noted

Symbol	Parameter	Test Condition	Min	Typ.	Max.	Units
RESISTIVE LOAD SWITCHING (D.C. $\leq 10\%$ , Pulse Width=40 $\mu\text{s}$ )						
$t_{\text{ON}}$	Turn On Time	$I_C=2.5\text{A}$ , $I_{B1}=500\text{mA}$ , $I_{B2}=-1\text{A}$ , $V_{\text{CC}}=250\text{V}$ , $R_L = 100\Omega$		500	750	ns
$t_{\text{STG}}$	Storage Time		1.2		1.5	$\mu\text{s}$
$t_{\text{F}}$	Fall Time			100	200	ns
$t_{\text{ON}}$	Turn On Time	$I_C=2\text{A}$ , $I_{B1}=400\text{mA}$ , $I_{B2}=-1\text{A}$ , $V_{\text{CC}}=300\text{V}$ , $R_L = 150\Omega$		100	150	ns
					150	ns
$t_{\text{STG}}$	Storage Time			1.4	2.2	$\mu\text{s}$
				1.7		$\mu\text{s}$
$t_{\text{F}}$	Fall Time			90	150	ns
				150		ns
$t_{\text{ON}}$	Turn On Time	$I_C=2.5\text{A}$ , $I_{B1}=500\text{mA}$ , $I_{B2}=-5\text{mA}$ , $V_{\text{CC}}=300\text{V}$ , $R_L = 120\Omega$		120	150	ns
					150	ns
$t_{\text{STG}}$	Storage Time		1.8		2.1	$\mu\text{s}$
				2.6		$\mu\text{s}$
$t_{\text{F}}$	Fall Time			110	150	ns
				160		ns
INDUCTIVE LOAD SWITCHING ( $V_{\text{CC}}=15\text{V}$ )						
$t_{\text{STG}}$	Storage Time	$I_C=2.5\text{A}$ , $I_{B1}=500\text{mA}$ , $I_{B2}=-0.5\text{A}$ , $V_Z=350\text{V}$ , $L_C=300\mu\text{H}$		1.9	2.2	$\mu\text{s}$
					2.4	$\mu\text{s}$
$t_{\text{F}}$	Fall Time			160	200	ns
				330		ns
$t_{\text{C}}$	Cross-over Time			350	500	ns
				750		ns
$t_{\text{STG}}$	Storage Time	$I_C=2\text{A}$ , $I_{B1}=400\text{mA}$ , $I_{B2}=-0.4\text{A}$ , $V_Z=300\text{V}$ , $L_C=200\mu\text{H}$	1.95		2.25	$\mu\text{s}$
				2.9		$\mu\text{s}$
$t_{\text{F}}$	Fall Time			120	150	ns
				270		ns
$t_{\text{C}}$	Cross-over Time			300	450	ns
				700		ns
$t_{\text{STG}}$	Storage Time	$I_C=1\text{A}$ , $I_{B1}=100\text{mA}$ , $I_{B2}=-0.5\text{A}$ , $V_Z=300\text{V}$ , $L_C=200\mu\text{H}$		0.6	0.8	$\mu\text{s}$
				1.0		$\mu\text{s}$
$t_{\text{F}}$	Fall Time			70		ns
				110		ns
$t_{\text{C}}$	Cross-over Time			80	130	ns
				170		ns

## Typical Characteristics




Figure 1. Static Characteristic




Figure 2. DC current Gain




Figure 3. DC current Gain




Figure 4. Collector-Emitter Saturation Voltage




Figure 5. Collector-Emitter Saturation Voltage






Figure 6. Base-Emitter Saturation Voltage


### Typical Characteristics (Continued)




**Figure 7. Base-Emitter Saturation Voltage**




**Figure 8. Collector Output Capacitance**




**Figure 9. Forward Recovery Time**



**Figure 10. Switching Time**




**Figure 11. Induction Storage Time**




**Figure 12. Inductive Crossover Time**


### Typical Characteristics (Continued)




**Figure 13. Inductive Fall Time**




**Figure 14. Safe Operating Area**



**Figure 15. Reverse Bias Safe Operating**




**Figure 16. Power Derating**



**Figure 17. RBSOA Saturation**

# Physical Dimensions

## TO-220



Dimensions in Millimeters



**TRADEMARKS**

The following includes registered and unregistered trademarks and service marks, owned by Fairchild Semiconductor and/or its global subsidiaries, and is not intended to be an exhaustive list of all such trademarks.

AccuPower™	F-PFS™	Power-SPM™	 <b>SYSTEM GENERAL</b> The Power Franchise® the <b>power</b> franchise TinyBoost™ TinyBuck™ TinyCalc™ TinyLogic® TINYOPTO™ TinyPower™ TinyPWM™ TinyWire™ TriFault Detect™ TRUECURRENT™* µSerDes™  SerDes™ UHC® Ultra FRFET™ UniFET™ VCX™ VisualMax™ XS™
Auto-SPM™	FRFET®	PowerTrench®	
Build it Now™	Global Power Resource <sup>SM</sup>	PowerXS™	
CorePLUS™	Green FPS™	Programmable Active Droop™	
CorePOWER™	Green FPS™ e-Series™	QFET®	
CROSSVOLT™	Gmax™	QS™	
CTL™	GTO™	Quiet Series™	
Current Transfer Logic™	IntelliMAX™	RapidConfigure™	
DEUXPEED®	ISOPLANAR™	 ™	
Dual Cool™	MegaBuck™	Saving our world, 1mW/W/kW at a time™	
EcoSPARK®	MICROCOUPLER™	SignalWise™	
EfficientMax™	MicroFET™	SmartMax™	
ESBC™	MicroPak™	SMART START™	
 Fairchild®	MicroPak2™	SPM®	
Fairchild Semiconductor®	MillerDrive™	STEALTH™	
FACT Quiet Series™	MotionMax™	SuperFET™	
FACT®	Motion-SPM™	SuperSOT™-3	
FAST®	OptoHiT™	SuperSOT™-6	
FastvCore™	OPTOLOGIC®	SuperSOT™-8	
FETBench™	OPTOPLANAR®	SupreMOS®	
FlashWriter®*	 ™	SyncFET™	
FPS™	PDP SPM™	Sync-Lock™	

\* Trademarks of System General Corporation, used under license by Fairchild Semiconductor.

**DISCLAIMER**

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

**LIFE SUPPORT POLICY**

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
2. A critical component in any component of a life support, device, or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

**ANTI-COUNTERFEITING POLICY**

Fairchild Semiconductor Corporation's Anti-Counterfeiting Policy. Fairchild's Anti-Counterfeiting Policy is also stated on our external website, [www.fairchildsemi.com](http://www.fairchildsemi.com), under Sales Support.

Counterfeiting of semiconductor parts is a growing problem in the industry. All manufacturers of semiconductor products are experiencing counterfeiting of their parts. Customers who inadvertently purchase counterfeit parts experience many problems such as loss of brand reputation, substandard performance, failed applications, and increased cost of production and manufacturing delays. Fairchild is taking strong measures to protect ourselves and our customers from the proliferation of counterfeit parts. Fairchild strongly encourages customers to purchase Fairchild parts either directly from Fairchild or from Authorized Fairchild Distributors who are listed by country on our web page cited above. Products customers buy either from Fairchild directly or from Authorized Fairchild Distributors are genuine parts, have full traceability, meet Fairchild's quality standards for handling and storage and provide access to Fairchild's full range of up-to-date technical and product information. Fairchild and our Authorized Distributors will stand behind all warranties and will appropriately address any warranty issues that may arise. Fairchild will not provide any warranty coverage or other assistance for parts bought from Unauthorized Sources. Fairchild is committed to combat this global problem and encourage our customers to do their part in stopping this practice by buying direct or from authorized distributors.

**PRODUCT STATUS DEFINITIONS**

**Definition of Terms**

Datasheet Identification	Product Status	Definition
Advance Information	Formative / In Design	Datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	Datasheet contains preliminary data; supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design.
No Identification Needed	Full Production	Datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve the design.
Obsolete	Not In Production	Datasheet contains specifications on a product that is discontinued by Fairchild Semiconductor. The datasheet is for reference information only.

ON Semiconductor and  are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at [www.onsemi.com/site/pdf/Patent-Marking.pdf](http://www.onsemi.com/site/pdf/Patent-Marking.pdf). ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that ON Semiconductor was negligent regarding the design or manufacture of the part. ON Semiconductor is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

## PUBLICATION ORDERING INFORMATION

### LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor  
19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA  
**Phone:** 303-675-2175 or 800-344-3860 Toll Free USA/Canada  
**Fax:** 303-675-2176 or 800-344-3867 Toll Free USA/Canada  
**Email:** [orderlit@onsemi.com](mailto:orderlit@onsemi.com)

**N. American Technical Support:** 800-282-9855 Toll Free  
USA/Canada  
**Europe, Middle East and Africa Technical Support:**  
Phone: 421 33 790 2910  
**Japan Customer Focus Center**  
Phone: 81-3-5817-1050

**ON Semiconductor Website:** [www.onsemi.com](http://www.onsemi.com)  
**Order Literature:** <http://www.onsemi.com/orderlit>  
For additional information, please contact your local  
Sales Representative