



- ► Low Profile
- Wide Frequency range
- Extended temperature range
- Built-in load capacitance
- RoHS Compliant (Note 7 Exemption)

ZTT Series Ceramic Resonator

built-in load capacitance.

The ZTT Series ceramic resonator offers a wide frequency range and extended temperature range capabilities with

OPERATING CONDITIONS / ELECTRICAL CHARACTERISTICS

PART NUMBER *	FREQUENCY RANGE (MHz)	FREQUENCY ACCURACY @ 25°C(%)	STABILITY IN TEMPERATURE -20~ +80°C (%)	AGING FOR TEN YEARS (%)	RESONANT RESISTANCE (Ω) MAX
ZTT□.□□MG	2.00 ~ 2.99	±0.5	±0.3	±0.3	80
ZTT□.□□MG	3.00 ~ 3.49	±0.5	±0.3	±0.3	50
ZTT□.□□MG	3.50 ~ 8.00	±0.5	±0.3	±0.3	30
ZTT□.□□MT	6.01 ~ 6.99	±0.5	±0.3	±0.3	30
ZTT□□.□□MT	7.00 ~ 13.00	±0.5	±0.3	±0.3	25
ZTT□□.□□MX	13.01 ~ 50.00	±0.5	±0.3	±0.3	30

[·] Withstanding voltage (5 seconds max.): 100V DC

PACKAGE DIMENSIONS (mm)




Figure 1) ZTT MG, Side and Front views





Figure 3) ZTT ... MT, MX Side and Front views

PART NUMBERING GUIDE: Example ZTT-4.00MG






Figure 2) ZTT□.□ MG Test Circuit




Figure 4) ZTT ... MT & ZTT ... MX Test Circuit

Note: ECS does not approve the use of it's products in Automotive, Military, Avionics, Life Sustaining or Life Support systems or any other related medical applications without written approval from ECS INC.

[·] Insulation Resistance 100M Ω Min. (at 10 V DC)