Features

Unregulated Converters

- Micro Size SIP 6 Package
- Industry Standard Pinout
- Power Sharing on Dual Output Version
- **3kVDC Isolation**
- **Optional Continuous Short Circuit Protected**
- Efficiency to 85 %

Description

The RBM Micro Size DC/DC-Converter complements Recom's industrial range of converters. This range is widely used for pcb distributed power systems and combines small package size, high efficiency, 3kVDC isolation and low output ripple.

The extended operating temperature range covering -40°C to $+85^{\circ}\text{C}$ is a standard feature. The full rated power can be taken from a single pin of this dual output converter, provided this does not exceed 1 Watt.

Selection Guide						
Part Number SIP 6 Micro Size	Input Voltage (VDC)	Output Voltage (VDC)	Output Current (mA)	Efficiency (%)	Max Capacitive Load (1)	
RBM-xx05S	5, 12	5	200	70-78	1000μF	
RBM-xx12S	5, 12	12	83	78-80	470µF	
RBM-xx15S	5, 12	15	66	80-84	470µF	
RBM-xx05D	5, 12	±5	±100	74-78	±470µF	
RBM-xx12D	5, 12	±12	±41	80-82	±220μF	
RBM-xx15D	5, 12	±15	±33	80-84	±220µF	

xx = Input Voltage. Other input and output voltage combinations available on request.

^{*} add Suffix "P" for Continuous Short Circuit Protection, e.g. RBM-0505S/P, RBM-0505D/P

Considerations	/	0500		and the second	6 11 1 1	
Specifications	(measured at 17	$x = 25^{\circ} G$. nominai	indut voitage.	ituli load an	d atter warm-up)

Input Voltage Range	±10%			
Output Voltage Accuracy	±5%			
Line Voltage Regulation	1.2%/1% of Vin typ.			
5 5	5V output type 15% max			
(10% to 100% full load)	12, 15V output types 10% max			
Output Ripple and Noise (20MHz limited)	100mVp-p max.			
Operating Frequency	50kHz min. / 100kHz typ. / 105kHz max.			
Efficiency at Full Load	70% min. / 80% typ.			
Minimum Load = 0%	Specifications valid for 10% minimum load only.			
Isolation Voltage	(tested for 1 second) 3000VDC			
	(rated for 1 minute**) 1500VAC / 60Hz			
Isolation Capacitance	20pF min. / 65pF max.			
Isolation Resistance	15 G Ω min.			
Short Circuit Protection	1 Second			
P-Suffix	Continuous			
Operating Temperature Range (free air convec	tion) -40°C to +85°C (see Graph)			
Storage Temperature Range	-55°C to +125°C			
Relative Humidity	95% RH			
Package Weight	1.3g			
Packing Quantity	30 pcs per Tube			
MTBF (+25°C) \ \ Detailed Information see	using MIL-HDBK 217F 1005 x 10 ³ hours			
(+85°C) ∫ Application Notes chapter "M7	TBF" using MIL-HDBK 217F 195 x 10 ³ hours			
Certifications				

CB Test Report Report: US/15348/UL IEC 60950-1:2005 2nd Ed. **UL** General Safety Report: E358085 UL 60950-1 2nd Ed. **EN General Safety** Report: SPCLVD1109103 EN60950-1:2001 + A11:2004 **EN Medical Safety** Report: MDD1205098-4 + RM1205098-4IEC/EN 60601-1 3rd Edition

Medical Report + ISO14971 Risk Assessment

ECONOLINE

DC/DC-Converter with 3 year Warranty




1 Watt SIP 6 Micro Size, Single & **Dual Output**



EN-60950-1 Certified UL-60950-1 Certified EN-60601-1 Certified

Derating-Graph

(Ambient Temperature)



^{**}Any data referred to in this datasheet are of indivative nature and based on our practical experience only. For further details, please refer

Refer to Application Notes

RBM

ECONOLINE

DC/DC-Converter

RBM Series

Specifications (measured at $T_A = 25$ °C, nominal input voltage, full load and after warm-up)


Notes


Note 1

Maximum capacitive load is defined as the capacitive load that will allow start up in under 1 second without damage to the converter.


Typical Characteristics


RBM-xx05S







RBM-xx12S







RBM-xx05D






RBM-xx12D







RBM


RBM-xx15S






RBM-xx15D





Package Style and Pinning (mm)

SIP6 Micro Size Package











Recommended Footprint Details





Pin Connections

Pin #	Single	Dual
1	+Vin	+Vin
2	–Vin	–Vin
4	NC	–Vout
5	-Vout	Com
6	+Vout	+Vout

NC = No Connection XX.X \pm 0.5 mm XX.XX \pm 0.25 mm

The product information and specifications are subject to change without prior notice. RECOM products are not authorized for use in safety-critical applications (such as life support) without RECOM's explicit written consent. A safety-critical application is defined as an application where a failure of a RECOM product may reasonably be expected to endanger or cause loss of life, inflict bodily harm or damage property. The buyer shall indemnify and hold harmless RECOM, its affiliated companies and its representatives against any damage claims in connection with the unauthorized use of RECOM products in such safety-critical applications.